



## 2.2-5 Female to N Male Low PIM RF Adapter | 123-JFNM | 123e.com

Part Number: 123-JFNM

2.2-5 Female to N Male RF adapters are used to either change the gender from one connector type to another, to mate different connector types together, or as disposable interfaces for test and measurement applications where main launch cables need protection from wear and tear. 123eWireless RF adapters are designed for low loss with maximum mating cycles without degradation.

### CROSS REFERENCE

Alternative To TA-JFNM, PE9797, AD-NP225J-1

### PHYSICAL SPECIFICATIONS

Connector A 2.2-5 Female

Connector B N MALE

### ELECTRICAL SPECIFICATIONS

Frequency Range DC-8GHz

Impedance 50 ohm

PIM  $\leq 160\text{dBc}$  @ 1800MHz

VSWR  $\leq 1.15$  @3GHz,  $\leq 1.25$  @3GHz-6GHz

### ENVIRONMENTAL SPECIFICATIONS

Operating Temperature  $-40^{\circ}\text{C}$  to  $+155^{\circ}\text{C}$

RoHS Compliance Yes

Thank you visiting 123eWireless.

Please contact us at [sales@123ewireless.com](mailto:sales@123ewireless.com) for any queries.