

**2.2-5 Female to N Male Low PIM RF Adapter | 123-JFNM | 123e.com**  
Part Number: 123-JFNM

2.2-5 Female to N Male RF adapters are used to either change the gender from one connector type to another, to mate different connector types together, or as disposable interfaces for test and measurement applications where main launch cables need protection from wear and tear. 123eWireless RF adapters are designed for low loss with maximum mating cycles without degradation.

**CROSS REFERENCE**

Alternative To	TA-JFNM, PE9797, AD-NP225J-1
----------------	------------------------------

**ELECTRICAL SPECIFICATIONS**

Frequency Range	DC-8GHz
Impedance	50 ohm
PIM	≤160dBc @ 1800MHz
VSWR	≤1.15 @3GHz, ≤1.25 @3GHz-6GHz

**ENVIRONMENTAL SPECIFICATIONS**

Operating Temperature	-40°C to +155°C
RoHS Compliance	Yes

**PHYSICAL SPECIFICATIONS**

Connector A	2.2-5 Female
Connector B	N MALE

Thank you visiting 123eWireless.

Please contact us at [sales@123ewireless.com](mailto:sales@123ewireless.com) for any queries.