



**2.2-5 Male to N Female Low PIM RF Adapter | 123-123-JMNF | 123e.com**  
Part Number: 123-JMNF

2.2-5 male to N female RF adapters are used to either change the gender from one connector type to another, to mate different connector types together or as disposable interfaces for test and measurement applications where main launch cables need protection from wear and tear. 123eWireless RF adapters are designed for low loss with maximum mating cycles without degradation.

#### CROSS REFERENCE

Alternative To	TA-JMNF, PE9794
----------------	-----------------

#### PHYSICAL SPECIFICATIONS

Mating Cycles	500
Connector A	2.2-5 male
Connector B	N female

#### ELECTRICAL SPECIFICATIONS

Frequency Range	DC-8GHz
Impedance	50 ohm
PIM	< -160dBc @700MHz, < -165dBc @1800MHz
VSWR	≤1.15 @3GHz, ≤1.25 @3GHz-6GHz

#### ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-40°C to +155°C
RoHS Compliance	Yes
Weather Standard	IEC 60068 55/155/21

Thank you visiting 123eWireless.

Please contact us at [sales@123ewireless.com](mailto:sales@123ewireless.com) for any queries.