

**4.3-10 Female to 2.2-5 Male RF Adapter | 123-HFJM | 123e.com**  
Part Number: 123-HFJM



4.3-10 Female to Male Adapter RF coaxial adapter is used to change the gender from one connector type to another, to mate different connector types together or as a disposable interface for test and measurement applications where main launch cables need protection from wear and tear. 123eWireless RF adapters are designed for low loss with maximum mating cycles without degradation.

**CROSS REFERENCE**

Alternative To	RFD-225M-43F
----------------	--------------

**PHYSICAL SPECIFICATIONS**

Mating Cycles	100
Connector A	4.3-10 Female
Connector B	2.2-5 Male

**ELECTRICAL SPECIFICATIONS**

Frequency Range	DC-6Ghz
Impedance	50 ohm
Insertion Loss	0.05dB
PIM	≤ -160 dBc
Return Loss	1.10 Max @4-6GHz

**ENVIRONMENTAL SPECIFICATIONS**

Operating Temperature	-55°C to +90°C
Weather Standard	IEC 60068 55/155/21

Thank you visiting 123eWireless.

Please contact us at [sales@123ewireless.com](mailto:sales@123ewireless.com) for any queries.