

**2.2-5 Female to N Male Low PIM RF Adapter | 123-JFNM | 123e.com**
Part Number: 123-JFNM

2.2-5 Female to N Male RF adapters are used to either change the gender from one connector type to another, to mate different connector types together, or as disposable interfaces for test and measurement applications where main launch cables need protection from wear and tear. 123eWireless RF adapters are designed for low loss with maximum mating cycles without degradation.

CROSS REFERENCE

Alternative To	TA-JFNM, PE9797, AD-NP225J-1
----------------	------------------------------

PHYSICAL SPECIFICATIONS

Connector A	2.2-5 Female
Connector B	N MALE

ELECTRICAL SPECIFICATIONS

Frequency Range	DC-8GHz
Impedance	50 ohm
PIM	≤160dBc @ 1800MHz
VSWR	≤1.15 @3GHz, ≤1.25 @3GHz-6GHz

ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-40°C to +155°C
RoHS Compliance	Yes

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.