



**1.0/2.3 Male to N Female RF Adapter | 123-1023MNF | 123e.com**  
Part Number: 123-1023MNF

1.0/2.3 male to N female RF Adapters are used to either change the gender from one connector type to another, to mate different connector types together or as disposable interfaces for test and measurement applications

#### PHYSICAL SPECIFICATIONS

Mating Cycles	500
Connector A	1.0/2.3 male
Connector B	N female

#### ELECTRICAL SPECIFICATIONS

Impedance	50 ohm
Insertion Loss	< 0.05 dB
VSWR	< 1.10
Frequency Range	DC-3Ghz

#### ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-55°C to +155°C
RoHS Compliance	Yes
Weather Standard	IEC 60068 55/155/21

Thank you visiting 123eWireless.

Please contact us at [sales@123ewireless.com](mailto:sales@123ewireless.com) for any queries.