



4.1-9.5 Female to N Male RF Adapter | 123-MDFNM-P | 123e.com
Part Number: 123-MDFNM-P

4.1-9.5 Female to N male RF Adapters are used to either change the gender from one connector type to another, to mate different connector types together, or as disposable interfaces for test and measurement applications.

CROSS REFERENCE

Alternative To RFN-1048-4, SM8224, PE91219, 1416

PHYSICAL SPECIFICATIONS

Mating Cycles 500
Connector A 4.1-9.5 Female
Connector B N Male

ELECTRICAL SPECIFICATIONS

Frequency Range DC-3GHz
Impedance 50 ohm
Insertion Loss ≤ 0.1 dB
PIM ≤ -160 dBc
VSWR ≤ 1.10 @3GHz

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.