

**4.3/10 Female to N Female RF Adapter | 123-HFNF | 123e.com**
Part Number: 123-HFNF

4.3/10 Female to N Female Adapters are used to either change the gender from one connector type to another, to mate different connector types together, or as disposable interfaces for test and measurement applications where main launch cables need protection from wear and tear. 123eWireless RF adapters are designed for low loss with maximum mating cycles without degradation.

CROSS REFERENCE

Alternative To

PHYSICAL SPECIFICATIONS

Mating Cycles	500
Connector A	4.3-10 Female
Connector B	N Female

ELECTRICAL SPECIFICATIONS

Frequency Range	DC-3Ghz
Impedance	50 ohm
PIM	≤ -166 dBc
VSWR	0-6 GHz ≤ 1.06

ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-40°C to +85°C
Weather Standard	IEC 60068 55/155/21

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.