

**4.3/10 Male to NEX10 Female RF Adapter | 123-HMXF | 123e.com**
Part Number: 123-HMXF

4.3/10 male to NEX10® female RF coaxial adapter is used to change the gender from one connector type to another, to mate different connector types together or as a disposable interface for test and measurement applications where main launch cables need protection from wear and tear. 123eWireless RF adapters are designed for low loss with maximum mating cycles without degradation.

CROSS REFERENCE

Alternative To	R191633016
----------------	------------

PHYSICAL SPECIFICATIONS

Mating Cycles	100
Connector A	4.3-10 Male
Connector B	NEX10 Female

ELECTRICAL SPECIFICATIONS

Frequency Range	DC-6Ghz
Impedance	50 ohm
PIM	≤ -166 dBc
VSWR	0-6 GHz ≤1.02

ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-55°C to +155°C
Weather Standard	IEC 60068 55/155/21

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.