



**1/4" Super Flex QMA Male Right Angle to Nex10 Male Low PIM jumper |**  
**123-14SFQMARXM | 123e.com**  
Part Number: 123-14SFQMARXM-XX-P

QMA Male Right Angle to Nex10 Male welded onto 1/4 inch Super Flexible jumper cable MADE IN THE USA. This small cell or DAS jumper is designed with few internal components which in turn reduces the inter-modulation distortion (IMD) averaging -165dBc. Each jumper is individually tested and certified to guarantee performance.

#### CROSS REFERENCE

Alternative To

#### PHYSICAL SPECIFICATIONS

|                        |                      |
|------------------------|----------------------|
| Connector A            | QMA Male Right Angle |
| Connector B            | Nex10 Male           |
| Outer Diameter         | 0.252in              |
| Jacket Color           | Black                |
| Jacket Material        | PE - UV Resistant    |
| Maximum Bending Radius | 0.78"                |

#### ELECTRICAL SPECIFICATIONS

|                 |                            |
|-----------------|----------------------------|
| Frequency Range | 600-3000 Mhz               |
| Impedance       | 50 Ohm                     |
| PIM             | -178 dBc                   |
| Return Loss     | ≤-27dB @3GHz, ≤-24dB @6GHz |

#### ENVIRONMENTAL SPECIFICATIONS

|                       |                  |
|-----------------------|------------------|
| Operating Temperature | -40°C to +85°C   |
| Weather Standard      | IEC 68 40/85/ 21 |

Thank you visiting 123eWireless.

Please contact us at [sales@123ewireless.com](mailto:sales@123ewireless.com) for any queries.