



4.3-10 Male 1/2" Superflexible Field Installed|123-2HM | 123e.com
Part Number: 123-2HM

4.3-10 male field termination connector with captivated cent pin for 1/2" Superflexible Helical cable. This connector is easily installed on to 123eWireless' 123-2-50 cable and/or any other manufacturer's 1/2" super flexible cable including Commscope FSJ4-50 and RFS SCF12-50J. This connector uses two wrenches and a stripping tool 123-2AS to install on to the cable.

CROSS REFERENCE

Alternative To

PHYSICAL SPECIFICATIONS

Options	Field Terminated on 1/2" Superflex cable (FSJ4-50B equivalent)
Connector A	4.3-10
Gender	Male
Inner Conductor	SPRING COPPER
Outer Conductor	BRASS
Insulation	TPX

ELECTRICAL SPECIFICATIONS

Frequency Range	DC-3GHz
Impedance	50 Omhs
PIM	< -160 dBc

ENVIRONMENTAL SPECIFICATIONS

RoHS Compliance	Yes
Weather Standard	IEC 60068 40 / 085/ 21

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.