



2.2-5 Male 1/4in Superflexible Field Installed Connector |123-14SFJM | 123e.com

Part Number: 123-14SFJM

2.2-5 Male 1/4" Superflexible FSJ1-50A Field Installed connector for 1/4" Super flexible annular cable 123-14SF-50 or equivalent. This connector is easily installed on to any manufacturer's 1/4" Superflexible cable including Commscope FSJ1-50A, and RFS SCF14-50J. This field termination design uses two wrenches and a stripping tool to install on to the cable

PHYSICAL SPECIFICATIONS

| | |
|-----------------|---------------------------------|
| Connector A | 2.2-5 |
| Gender | MALE |
| Inner Conductor | Phosphor Bronze, Silver Plating |
| Body | Brass, Ternary Alloy Plating |
| Gasket | Silicone Rubber |
| Insulation | PTFE |

ELECTRICAL SPECIFICATIONS

| | |
|-----------------|---------------------------|
| Frequency Range | 0- 6GHz |
| Impedance | 50 ohms |
| PIM | -160dBc |
| VSWR | 1.15(0~3GHz) 1.30[3-6GHz) |

ENVIRONMENTAL SPECIFICATIONS

| | |
|-----------------------|----------------|
| Operating Temperature | -50°C to 155°C |
| RoHS Compliance | Yes |

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.