



2.2-5 Male 1/4" Superflexible Field Installed Connector | 123-14SFJM | 123e.com
Part Number: 123-14SFJM

2.2-5 Male 1/4" Superflexible FSJ1-50A Field Installed connector for 1/4" Super flexible annular cable 123-14SF-50 or equivalent. This connector is easily installed on to any manufacturer's 1/4" Superflexible cable including Commscope FSJ1-50A, and RFS SCF14-50J. This field termination design uses two wrenches and a stripping tool to install on to the cable

PHYSICAL SPECIFICATIONS

Connector A	2.2-5
Gender	MALE
Inner Conductor	Phosphor Bronze, Silver Plating
Body	Brass, Ternary Alloy Plating
Gasket	Silicone Rubber
Insulation	PTFE

ELECTRICAL SPECIFICATIONS

Frequency Range	0- 6GHz
Impedance	50 ohms
PIM	-160dBc
VSWR	1.15(0~3GHz) 1.30[3-6GHz)

ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-50°C to 155°C
RoHS Compliance	Yes

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.