



N Female to NEX10 Male RF Adapter | 123-NFXM | 123e.com
Part Number: 123-NFXM

N Female to NEX10 Male RF coaxial adapter is used to change the gender from one connector type to another, to mate different connector types together or as a disposable interface for test and measurement applications where main launch cables need protection from wear and tear. 123eWireless RF adapters are designed for low loss with maximum mating cycles without degradation.

CROSS REFERENCE

Alternative To R191630007, 227006, RAYN/NEX10-KJ

PHYSICAL SPECIFICATIONS

Mating Cycles 100
Connector A N Female
Connector B NEX10 Male

ELECTRICAL SPECIFICATIONS

Frequency Range DC-11Ghz
Impedance 50 ohm
Insertion Loss 0.05 √F(GHz) dB Max
PIM PIM<=-123dBm, 2 carriers of +43dBm
VSWR 1.02 + 0.0150 x F(GHz) Max

ENVIRONMENTAL SPECIFICATIONS

Operating Temperature -55~+125 °C
Weather Standard IEC 60068 55/155/21

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.