



N Male to N Female 6dB 100 Watts Attenuator | 123-N6DB100W | 123e.com
Part Number: 123-N6DB100W

N (M) to N (F) 6dB 100 Watts Attenuator Fixed attenuators are used to lower voltage, dissipate power, and to improve impedance matching.

- ◆ Wide Frequency Band DC 6GHz
- ◆ 2G/3G/4G/LTE Coverage
- ◆ Low attenuation accuracy
- ◆ Widely used for In building Solutions

CROSS REFERENCE

Alternative To

PHYSICAL SPECIFICATIONS

Connector A	N Male
Connector B	N Female

ELECTRICAL SPECIFICATIONS

Attenuation	6dB \pm 1.0
Average Power	100w@20C
Frequency Range	DC-6GHz
Impedance	50 ohm
VSWR	\leq 1.30

ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-30C ~+70C
-----------------------	------------

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.