



## NEX10 Male 40 Watt RF Load Terminator | 123-XMT40 | 123e.com

Part Number: 123-XMT40

The NEX10 Male 40 Watt RF Load Terminator (123-XMT20) is designed to safely terminate radio frequency signals in communication systems. It features a NEX10 male connector, operates across a DC to 6 GHz frequency range, and handles up to 40 watts of average power. With an impedance of 50 ohms and a VSWR of  $\leq 1.25$ , it ensures minimal signal reflection. The terminator is built to withstand operating temperatures from -25°C to 65°C and meets IEC 60068 40/085/21 and IP67 weather standards, making it suitable for various environmental conditions.

### CROSS REFERENCE

Alternative To

### PHYSICAL SPECIFICATIONS

Connector A	Nex10
Gender	Male

### ELECTRICAL SPECIFICATIONS

Average Power	40 Watts
Frequency Range	DC-6Ghz
Impedance	50 ohm
VSWR	$\leq 1.25$

### ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-25 to 65C
Weather Standard	IEC 60068 40 / 085/ 21; IP67

Thank you visiting 123eWireless.

Please contact us at [sales@123ewireless.com](mailto:sales@123ewireless.com) for any queries.