

**Nex10 Male Right Angle 1/4in Superflexible Field Installed |123-14SFXMR | 123e.com**  
Part Number: 123-14SFXMR



Nex10 Male Right Angle 1/4" Superflexible FSJ1-50A Field Installed connector for 1/4" Super flexible annular cable 123-14SF-50 or equivalent. This connector is easily installed on to any manufacturer's 1/4" Superflexible cable including Commscope FSJ1-50A, and RFS SCF14-50J. This field termination design uses two wrenches and a stripping tool to install on to the cable

**CROSS REFERENCE**

Alternative To

**PHYSICAL SPECIFICATIONS**

|                 |                                 |
|-----------------|---------------------------------|
| Connector A     | Nex10                           |
| Gender          | MALE                            |
| Inner Conductor | Phosphor Bronze, Silver Plating |
| Body            | Brass, Ternary Alloy Plating    |
| Gasket          | Silicone Rubber                 |
| Insulation      | PTFE                            |

**ELECTRICAL SPECIFICATIONS**

|                 |                           |
|-----------------|---------------------------|
| Frequency Range | 0- 6GHz                   |
| Impedance       | 50 ohms                   |
| PIM             | -160dBc                   |
| VSWR            | 1.15(0~3GHz) 1.30[3-6GHz) |

**ENVIRONMENTAL SPECIFICATIONS**

|                       |                |
|-----------------------|----------------|
| Operating Temperature | -50°C to 155°C |
| RoHS Compliance       | Yes            |