



**4.3-10 Male to N Male RF Adapter | 123-HMNM | 123e.com**  
Part Number: 123-HMNM

4.3-10 male to N male RF adapters are used to either change the gender from one connector type to another, to mate different connector types together, or as disposable interfaces for test and measurement applications where main launch cables need protection from wear and tear. 123eWireless RF adapters are designed for low loss with maximum mating cycles without degradation.

#### CROSS REFERENCE

Alternative To FMAD1176, 1401, C8518

#### PHYSICAL SPECIFICATIONS

Mating Cycles 100  
Connector A 4.3-10 Male  
Connector B N Male

#### ELECTRICAL SPECIFICATIONS

Frequency Range DC-6Ghz  
Impedance 50 ohm  
Insertion Loss  $\leq 0.1\text{dB}$   
PIM  $\leq -160\text{ dBc}$   
VSWR 0-3 GHz  $\leq 1.10$

#### ENVIRONMENTAL SPECIFICATIONS

Operating Temperature  $-40^{\circ}\text{C}$  to  $+85^{\circ}\text{C}$

Thank you visiting 123eWireless.

Please contact us at [sales@123ewireless.com](mailto:sales@123ewireless.com) for any queries.