



N Male to N Male RF Adapter | 123-NMNM | 123e.com
Part Number: 123-NMNM

N Male to N Male RF Adapters are used to either change the gender from one connector type to another, to mate different connector types together or as disposable interfaces for test and measurement applications. Low PIM Rated

CROSS REFERENCE

Alternative To	CA-NMNM, 53S101-S00N5, R/FRFN1014-1
----------------	-------------------------------------

PHYSICAL SPECIFICATIONS

Mating Cycles	500
Connector A	N Male
Connector B	N Male
Insulation	PTFE

ELECTRICAL SPECIFICATIONS

Frequency Range	DC-3Ghz
Impedance	50 ohm
Insertion Loss	>0.05 dB
VSWR	1.08

ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-40 ~ +85 °C °C
Weather Standard	IEC 60068 55/155/21

Thank you visiting 123eWireless.

Please contact us at sales@123ewireless.com for any queries.