



**1.0/2.3 Male to N Female RF Adapter | 123-1023MNF | 123e.com**  
Part Number: 123-1023MNF

1.0/2.3 male to N female RF Adapters are used to either change the gender from one connector type to another, to mate different connector types together or as disposable interfaces for test and measurement applications

#### PHYSICAL SPECIFICATIONS

|               |              |
|---------------|--------------|
| Mating Cycles | 500          |
| Connector A   | 1.0/2.3 male |
| Connector B   | N female     |

#### ELECTRICAL SPECIFICATIONS

|                 |           |
|-----------------|-----------|
| Frequency Range | DC-3Ghz   |
| Impedance       | 50 ohm    |
| Insertion Loss  | < 0.05 dB |
| VSWR            | < 1.10    |

#### ENVIRONMENTAL SPECIFICATIONS

|                       |                     |
|-----------------------|---------------------|
| Operating Temperature | -55°C to +155°C     |
| RoHS Compliance       | Yes                 |
| Weather Standard      | IEC 60068 55/155/21 |

Thank you visiting 123eWireless.

Please contact us at [sales@123ewireless.com](mailto:sales@123ewireless.com) for any queries.