



**Din (7/16) Female to N Female RF adapter | 123-DFNF | 123e.com**  
Part Number: 123-DFNF

Din (7/16) Female to N female RF adapters are used to either change the gender from one connector type to another, to mate different connector types together, or as disposable interfaces for test and measurement applications where main launch cables need protection from wear and tear. 123eWireless RF adapters are designed for low loss with maximum mating cycles without degradation

#### CROSS REFERENCE

Alternative To	CA-TNFDf
----------------	----------

#### PHYSICAL SPECIFICATIONS

Mating Cycles	500
Connector A	7/16 DIN FEMALE
Connector B	N FEMALE
Inner Conductor	Ag
Insulation	PTFE

#### ELECTRICAL SPECIFICATIONS

Frequency Range	DC-6GHz
Impedance	50 ohm
PIM	≤160dBc
VSWR	≤1.15 @3GHz, ≤1.25 @3GHz-6GHz

#### ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-40°C to +85°C
Weather Standard	IEC 6855 / 155/ 56

Thank you visiting 123eWireless.

Please contact us at [sales@123ewireless.com](mailto:sales@123ewireless.com) for any queries.