



30412 Esperanza, Rancho Santa Margarita
CA 92688, (888) 263-6000
sales@123ewireless.com



SMA Female to NEX10 Male RF Adapter | 123-SMAFXM | 123e.Com

Part Number: 123-SMAFXM

SMA female to Nex10 Male RF Adapters are used to either change the gender from one connector type to another, to mate different connector types together or as disposable interfaces for test and measurement applications.

CROSS REFERENCE	
Alternative To	AD-N10PSMAJ-2, R191621007
ELECTRICAL SPECIFICATIONS	
Frequency Range	DC-0-8GHz
Impedance	50Ω
Inner Construction	Brass, Tri-Metal Plating
PIM	<-155dBc
VSWR	< 1.10 @3GHz - <1.25@3-6HGz, <1.30@6-8GHz
ENVIRONMENTAL SPECIFICATIO	NS
Operating Temperature	-40° ~ + 155°
RoHS Compliance	Yes
PHYSICAL SPECIFICATIONS	
Insulation	PTFE
Connector A	SMA Female
Connector B	NEX10 Male